

[Home](#) > [Docs](#) > [Datasheets](#) > [EVE 3](#) > EVE 3 4.3"

EVE 3 4.3"



This datasheet gives detailed information about the Riverdi 4.3" EVE3 displays. The displays come in different versions: with **capacitive, resistive, or no touchscreen**, with a decorative **cover glass**, as well as with or without a **metal mounting frame**.

ORDER NOW



Rev.1.0
2018-10-22

| ITEM | CONTENTS | UNIT |
|-------------------|---------------------------------|----------|
| LCD Type | TFT/Transmissive/Normally white | / |
| Size | 4.3 | Inch |
| Viewing Direction | 12:00 (without image inversion) | O' Clock |

| | | |
|--------------------------------|---------------------------------------|----------|
| Gray Scale Inversion Direction | 6:00 | O' Clock |
| Number of Dots | 480 x (RGB) x 272 | / |
| Driver IC | BT81x | / |
| Interface Type | SPI/QSPI | / |
| Module Memory Size | 1 MB (BT81x) + 64 Mb (external flash) | / |
| Brightness | no touch module | 550 |
| | CTP module | 500 |
| | RTP module | 440 |
| | | cd/m2 |
| Color Depth | 16.7M | / |
| Pixel Arrangement | RGB Vertical Stripe | / |
| Surface Treatment | Anti-glare / Clear (for CTP) | / |
| Input Voltage | 3.3 | V |

Note 1: RoHS, REACH SVHC compliant

Note 2: LCM weight tolerance: $\pm 5\%$.

Revision Record

| REV NO. | REVDATE | CONTENTS | REMARKS |
|---------|------------|-----------------|---------|
| 1.0 | 2018-10-22 | Initial Release | |

Table of Content

| | |
|--------------------------------------|---|
| 1. Module classification information | 10.1. Clock and data input time diagram |
| 2. Assembly guide – integration | 10.2. Parallel RGB timing table |
| 2.1. UxTouch assembly | 11 Touch panel specifications |
| 2.2. Mounting frame | 11.1. Electrical characteristics |
| 3. Module drawing | 11.1.1. For capacitive touch panel |
| 4. Absolute maximum ratings | 11.1.2. For resistive touch panel |
| 5. Electrical characteristics | 11.2. Mechanical characteristics |
| 6. Backlight characteristics | 11.2.1 For capacitive touch panel |
| 7. Electro-optical characteristics | 11.2.2. For resistive touch panel |
| 8 Interface description | 12 inspection |
| 9 BT8x Controller specifications | 12.1. Inspection condition |
| 9.1. Serial host interface | 12.2 Inspection standard |
| 9.2. Block diagram | 13 Reliability test |
| 9.3. Host Interface SPI mode 0 | |
| 9.4. Backlight driver block diagram | |

1. Module classification information

| RV | T | 43 | x | L | B | x | W | x | 00 |
|-----------|----------|-----------|----------|----------|----------|----------|----------|----------|-----------|
| 1. | 2. | 3. | 4. | 5. | 6. | 7. | 8. | 9. | 10. |


| | | |
|-----|-------------------------|---|
| 1. | BRAND | RV – Riverdi |
| 2. | PRODUCT TYPE | T – TFT Standard F – TFT Custom |
| 3. | DISPLAY SIZE | 43 – 4.3” |
| 4. | MODEL SERIAL NO. | A (A-Z) U – UxTouch |
| 5. | RESOLUTION | L– 480×272 px |
| 6. | INTERFACE | B – TFT + Controller BT81x |
| 7. | FRAME | N – No Frame F – Mounting Frame |
| 8. | BACKLIGHT TYPE | W – LED White |
| 9. | TOUCH PANEL | N – No Touch Panel R – Resistive Touch Panel C – Capacitive Touch Panel |
| 10. | VERSION | 00 (00-99) |

2. Assembly guide – integration

Three options of rear side adhesive tape are available: double side adhesive tape 0.2 mm with 3M 467MP glue, foam double side adhesive tape 0.5 mm with DST 3M 9495LE glue or without any tape.

There are also two versions of glass color: black and white.

Rear side adhesive tape options:

| | | |
|--|---|--|
|  |  |  |
| Double side adhesive tape with DST 3M 9495LE glue (total thickness 0.2mm) | Foam double side adhesive tape with 3M 9495LE glue (total thickness 0.5mm) | Without tape |

Cover glass color options:

| | |
|--|---|
|  |  |
| BLACK | WHITE |

Product options:


| NAME OF THE PRODUCT | PART NUMBER | DESCRIPTION |
|-----------------------|---------------|---|
| RiFT-43 | RVT43ALBNWN00 | BT816, no touch panel |
| RiFT-43-RES | RVT43ALBNWR00 | BT816, resistive touch panel |
| RiFT-43-CAP | RVT43ALBNWC00 | BT815, capacitive touch panel |
| RiFT-43- FR | RVT43ALBFWN00 | BT816, no touch panel, mounting frame |
| RiFT-43-RES-FR | RVT43ALBFWR00 | BT816, resistive touch panel, mounting frame |
| RiFT-43-CAP-FR | RVT43ALBFWC00 | BT815, capacitive touch panel, mounting frame |
| RiFT-43-CAP-UX | RVT43ULBNWC00 | BT815, uxTouch, black cover glass, 0.2mm DST |
| | RVT43ULBNWC01 | BT815, uxTouch, black cover glass, 0.5 mm DST |
| | RVT43ULBNWC02 | BT815, uxTouch, black cover glass, no DST |
| | RVT43ULBNWC03 | BT815, uxTouch, white cover glass, 0.2mm DST |
| | RVT43ULBNWC04 | BT815, uxTouch, white cover glass, 0.5 mm DST |

2.1. UxTouch assembly

UxTouch are LCD TFT displays with specially designed projected capacitive touch panels. UxTouch display can be mounted without any holed in the housing. Our standard UxTouch displays include double-sided adhesive tape (DST) to stick TFT easily to the housing. Basic series include 4.3", 5.0" and 7.0" display sizes.

UxTouch models with double-side adhesive tape (PN with endings 00, 01, 03, 04) can be mounted by connecting the glass to the housing. Riverdi recommends to use support brackets assembled to display's back. An additional support will stiffen the whole structure and minimize the influence of external factors such as vibration. Figure 1 and Figure 2 below show examples of using support elements.


Figure 1. Example of using support brackets




2.2. Mounting frame



For dimensions 3.5", 4.3", 5.0" and 7.0" the product with mounting frame version is available. Thanks to the four catches attached to the side, frame provides strong assembly to the surface by mounting element (like the screw, see Figure 2). The frames are specially designed to fit Riverdi products perfectly. The diameter of the mounting hole is 3.5mm.



Figure 2. Mounting frame





3. Module drawing









4. Absolute maximum ratings

| PARAMETER | SYMBOL | MIN | MAX | UNIT |
|---------------------------------|-----------------|-----|----------------|------|
| Supply Voltage for Logic | VDD | 0 | 4.0 | V |
| Supply Voltage for LED Inverter | BLVDD | 0 | 7.0 | V |
| Input Voltage for Logic | VIN | 0 | 4.0 | V |
| LED forward current (each LED) | IF | – | 25 | mA |
| Operating Temperature | T _{OP} | -20 | 70 | °C |
| Storage Temperature | T _{ST} | -30 | 80 | °C |
| Humidity | RH | – | 90% (Max 60°C) | RH |

5. Electrical characteristics

| PARAMETER | SYMBOL | MIN | TYP | MAX | UNIT | NOTES |
|-----------------------------------|------------------|--------|-----|--------|------|------------|
| Supply Voltage For Module | VDD | 3.0 | 3.3 | 3.6 | V | |
| Input Voltage for LED Inverter | BLVDD | 2.8 | 5.0 | 5.5 | V | |
| LED Backlight Current | IDDbacklight | – | 260 | 325 | mA | BLVDD=3.3V |
| LED Backlight Current | IDDbacklight | – | 150 | 187 | mA | BLVDD=5V |
| Input Voltage 'H' level | V _{IH} | 0.7VDD | – | VDD | V | |
| Input Voltage 'L' level | V _{IL} | 0 | – | 0.2VDD | V | |
| Input Current | I _{In} | | TBD | | mA | |
| Input Current for module with CTP | I _{InC} | | TBD | | mA | |

6. Backlight characteristics

| ITEM | SYMBOL | MIN | TYP | MAX | UNIT |
|------|--------|-----|-----|-----|------|
|------|--------|-----|-----|-----|------|

| | | | | | |
|---------------------------|-------|-------|-------|----|----------|
| Voltage for LED backlight | V_l | - | 16 | - | V |
| Current for LED backlight | I_l | - | 40 | 60 | mA |
| LED Life Time | - | 30000 | 50000 | - | H_{rs} |

Note: The LED Supply Voltage is defined by the numbers of LED at $T_a=25^\circ\text{C}$ and $I_L=40\text{mA}$.

7. Electro-optical characteristics

| ITEM | SYMBOL | | CONDITION | MIN | TYP | MAX | UNIT | REMARK | NOTE |
|----------------------------|----------------|----|--|-------|-------|-------|-------------------|----------|------|
| Response Time | Tr+Tf | | $\theta=0^\circ$ | - | 20 | 30 | ms | Figure 4 | 4 |
| Contrast Ratio | Cr | | | 320 | 400 | - | — | Figure 5 | 1 |
| Luminance Uniformity | δ WHITE | | $\theta=0^\circ$ | 80 | - | - | % | Figure 5 | 3 |
| Surface Luminance | TFT | Lv | $T_a=25$ | 440 | 550 | - | cd/m ² | Figure 5 | 2 |
| | TFT+CTP | | | 400 | 500 | - | | | |
| | TFT+RTP | | | 350 | 440 | - | | | |
| Viewing Angle Range | θ | | $\theta = 90^\circ$ | 35 | 50 | - | deg | Figure 6 | 6 |
| | | | $\theta = 270^\circ$ | 55 | 70 | - | deg | Figure 6 | |
| | | | $\theta = 0^\circ$ | 55 | 70 | - | deg | Figure 6 | |
| | | | $\theta = 180^\circ$ | 55 | 70 | - | deg | Figure 6 | |
| CIE (x, y) Chromaticity | Red | x | $\theta=0^\circ$ $\theta=0^\circ$ $T_a=25$ | 0.570 | 0.620 | 0.670 | Figure 6 | 5 | |
| | | y | | 0.294 | 0.344 | 0.394 | | | |
| | Green | x | | 0.256 | 0.306 | 0.356 | | | |
| | | y | | 0.513 | 0.563 | 0.613 | | | |
| | Blue | x | | 0.083 | 0.133 | 0.183 | | | |
| | | y | | 0.099 | 0.149 | 0.199 | | | |
| | White | x | | 0.250 | 0.300 | 0.350 | | | |
| | | y | | 0.280 | 0.330 | 0.380 | | | |

Note 1. Contrast Ratio(CR) is defined mathematically as below, for more information see Figure 4.

$$\text{Contrast Ratio} = \frac{\text{Average Surface Luminance with all white pixels (P1, P2, P3, P4, P5)}}{\text{Average Surface Luminance with all black pixels (P1, P2, P3, P4, P5)}}$$

Note 2. Surface luminance is the LCD surface from the surface with all pixels displaying white. For more information, see Figure 4.

$L_v = \text{Average Surface Luminance with all white pixels (P1, P2, P3, P4, P5)}$

Note 3. The uniformity in surface luminance δ_{WHITE} is determined by measuring luminance at each test position 1 through 5, and then dividing the maximum luminance of 5 points luminance by minimum luminance of 5 points luminance. For more information, see Figure 4 .

$$\delta_{\text{WHITE}} = \frac{\text{Minimum Surface Luminance with all white pixels (P1, P2, P3, P4, P5)}}{\text{Maximum Surface Luminance with all white pixels (P1, P2, P3, P4, P5)}}$$

Note 4. Response time is the time required for the display to transition from white to black (Rise Time, T_r) and from black to white (Decay Time, T_f). For additional information see FIG 1. The test equipment is Autronic-Melchers's ConoScope series.

Note 5. CIE (x, y) chromaticity, the x, y value is determined by measuring luminance at each test position 1 through 5, and then make average value.

Note 6. Viewing angle is the angle at which the contrast ratio is greater than 2. For TFT module the contrast ratio is greater than 10. The angles are determined for the horizontal or x axis and the vertical or y axis with respect to the z axis which is normal to the LCD surface. For more information see Figure 4.

Note 7. For viewing angle and response time testing, the testing data is based on Autronic-Melchers's ConoScope series. Instruments for Contrast Ratio, Surface Luminance, Luminance Uniformity, CIE the test data is based on TOPCON's BM-5 photo detector.

Note 8. For TFT module, Gray scale reverse occurs in the direction of panel viewing angle.

Figure 3. The definition of response time




Figure 4. Measuring method for Contrast ratio, surface luminance, Luminance uniformity, CIE (x, y) chromaticity





Figure 5. The definition of viewing angle



8. Interface description

| PIN NO. | SYMBOL | DESCRIPTION |
|---------|-----------|--|
| 1 | VDD | Power Supply |
| 2 | GND | Ground |
| 3 | SPI_SCLK | SPI SCK Signal, Internally 47k Pull UP |
| 4 | MISO/IO1 | SPI MISO Signal / SPI Quad mode: SPI data line 1 |
| 5 | MOSI/IO0 | SPI MOSI Signal / SPI Quad mode: SPI data line 0 |
| 6 | CS | SPI Chip Select Signal , Internally 47k Pull UP |
| 7 | INT | Interrupt Signal, Active Low, Internally 47k Pull UP |
| 8 | PD | Power Down Signal, Active Low, Internally 47k Pull UP |
| 9 | NC | Not Connected |
| 10 | AUDIO_OUT | Audio Out Signal |
| 11 | GPIO0/IO2 | SPI Single mode: General purpose IO0/ SPI Quad mode: SPI data line 2 |
| 12 | GPIO1/IO3 | SPI Single mode: General purpose IO1/ SPI Quad mode: SPI data line 3 |
| 13 | GPIO2 | General purpose IO2 |
| 14 | GPIO3 | General purpose IO3 or analog input for ADC |
| 15 | NC | Not Connected |

| | | |
|-----------|-------|---|
| 16 | NC | Not Connected |
| 17 | BLVDD | Backlight Power Supply, Can Be Connected to VDD |
| 18 | BLVDD | Backlight Power Supply, Can Be Connected to VDD |
| 19 | BLGND | Backlight Ground, Internally connected to GND |
| 20 | BLGND | Backlight Ground, Internally connected to GND |

9. BT8x Controller specifications

BT8x or EVE3 (Embedded Video Engine 3) simplifies the system architecture for advanced human machine interfaces (HMIs) by providing functionality for display, audio, and touch as well as an object oriented architecture approach that extends from display creation to the rendering of the graphics.

9.1. Serial host interface

Figure 6. SPI interface connection






Figure 7. QSPI interface connection



SPI Interface – the SPI slave interface operates up to 30MHz.


Only SPI mode 0 is supported. The SPI interface is selected by default (MODE pin is internally pulled low by 47k resistor).

9.2. Block diagram



9.3. Host Interface SPI mode 0

Figure 9. SPI timing diagram



For more information about BT8x controller please go to official BT8x website.


<https://www.ftdichip.com/Products/ICs/BT81X.html>

9.4. Backlight driver block diagram

Backlight enable signal is internally connected to BT8x Backlight control pin. This pin is controlled

by two BT8x's registers. One of them specifies the PWM output frequency, second one specifies the duty cycle. Refer to BT8x datasheet for more information.


Figure 10. Backlight driver block diagram



10. LCD timing characteristics

10.1. Clock and data input time diagram

Figure 11. Clock and data input time diagram



10.2. Parallel RGB timing table

| PARAMETER | SYMBOL | MIN | TYP | MAX | UNIT |
|------------------|--------|-----|-----|-----|------|
| DCLK Frequency | Fclk | 5 | 9 | 12 | MHz |
| VSD Period Time | Tv | 277 | 288 | 400 | H |
| VSD Display Area | Tvd | 272 | 272 | 272 | H |
| VSD Back Porch | Tvb | 3 | 8 | 31 | H |
| VSD Front Porch | Tvfp | 2 | 8 | 97 | H |
| HSD Period Time | Th | 520 | 525 | 800 | DCLK |
| HSD Display Area | Thd | 480 | 480 | 480 | DCLK |

| | | | | | |
|-----------------|------|----|----|-----|------|
| HSD Back Porch | Thbp | 36 | 40 | 255 | DCLK |
| HSD Front Porch | Thfp | 4 | 5 | 65 | DCLK |

11. Touch panel specifications

11.1. Electrical characteristics

Note: Avoid operating with hard or sharp material such as a ball point pen or a mechanical pencil except a polyacetal pen (tip R0.8mm or less) or a finger

11.1.1. For capacitive touch panel


| DESCRIPTION | | SPECIFICATION |
|-------------------------|-------------|----------------------|
| Operating Voltage | | DC 2.8~3.6V |
| Power Consumption (IDD) | Active Mode | 10~18mA |
| | Sleep Mode | 30~50 μ A |
| Interface | | I ² C |
| Linearity | | <1.5% |
| Controller | | FT5446 |
| I2C address | | 0x38 (7 bit address) |
| Resolution | | 1280*768 |

11.1.2. For resistive touch panel

| ITEM | VALUE | | | UNIT | REMARK |
|-----------------------|-------|------|------|------------|---------------------------|
| | Min. | Typ. | Max. | | |
| Linearity | -3.0 | - | 3.0 | % | Analog X and Y directions |
| Terminal Resistance | 400 | - | 1050 | Ω | X |
| | 100 | - | 450 | Ω | Y |
| Insulation Resistance | - | - | - | M Ω | DC DC 25V |
| Voltage | - | - | 10 | V | DCDC |
| Chattering | - | - | 10 | ms | 100k Ω pull-up |
| Transparency | 80 | - | - | % | JIS K7105 |

11.2. Mechanical characteristics

Note 1: Force test condition, Input DC 5V on X direction, Drop off Polyacetal Stylus (R0.8), until output voltage stabilize, then get the R8.0mm Silicon rubber and do finger Activation force test. Next step, 9 points.



Note 2: Measurement surface area conditions, Scratch 100,000 times straight line on the film with a stylus change every 20,000 times with Force: 250gf, Speed: 60mm/sec by R0.8 polaceteal stylus.

Note 3: Pitting test, Pit 1, 000, 000 times on the film with R0.8 silicon rubber with Force: 250gf and Speed: 2 times/sec.

11.2.1 for capacitive touch panel

| DESCRIPTION | INL SPECIFICATION | REMARK |
|----------------------------------|-------------------|--------------------|
| Touch Panel Size | 4.3 inch | |
| Outline Dimension (OD) | 103.1mm x 65.4mm | Cover Lens Outline |
| Outline Dimension (OD) – UxTouch | 120.38 x 79.20mm | |
| Product Thickness | 1.70mm | |
| Glass Thickness | 0.7 mm | |
| Ink View Area | 97.00mm x 55.50mm | |
| Sensor Active Area | 97.4mm x 56.40mm | |
| Input Method | 5 Finger | |
| Activation Force | Touch | |
| Surface Hardness | ≥7H | |

11.2.2. For resistive touch panel

Note 1: Force test condition, Input DC 5V on X direction, drop off Polyacetal Stylus (R0.8), until output voltage stabilize, then get the R8.0mm Silicon rubber and do finger Activation force test. Next step, 9 points.

| ITEM | VALUE | | | UNIT | REMARK |
|-------------------------------|---------------|------|------|------------|-----------|
| | Min. | Typ. | Max. | | |
| Activation Force | 80 | – | – | gf | Note 1 |
| Durability-Surface Scratching | Write 100,000 | – | – | characters | Note 2 |
| Durability-Surface Pitting | 1,000,000 | – | – | touches | Note 3 |
| Surface Hardness | 3 | – | – | H | JIS K5400 |

12. Inspection

Standard acceptance/rejection criteria for TFT module.

12.1. Inspection condition

Ambient conditions:


- Temperature: $25\pm^{\circ}\text{C}$
- Humidity: $(60\pm 10)\% \text{RH}$
- Illumination: Single fluorescent lamp non-directive (300 to 700 lux)

Viewing distance:

$35\pm 5\text{cm}$ between inspector bare eye and LCD.

Viewing Angle:


U/D: $45^{\circ}/45^{\circ}$, L/R $45^{\circ}/45^{\circ}$



12.2 Inspection standard

| Item | Criterion |
|------|-----------|
|------|-----------|

Black spots, white spots, light leakage, Foreign Particle (round Type)




$$D = \frac{(x + y)}{2}$$

*Spots density: 10 mm

| Size < 5" | |
|---------------------|---------------|
| Average Diameter | Qualified Qty |
| D < 0.2 mm | Ignored |
| 0.2 mm < D < 0.3 mm | 3 |
| 0.3 mm < D < 0.5 mm | 2 |
| 0.5 mm < D | 0 |

| Size >= 5" | |
|---------------------|---------------|
| Average Diameter | Qualified Qty |
| D < 0.2 mm | Ignored |
| 0.2 mm < D < 0.3 mm | 4 |
| 0.3 mm < D < 0.5 mm | 2 |
| 0.5 mm < D | 0 |

LCD black spots, white spots, light leakage (line Type)



*Spots density: 10 mm

| Size < 5" | | |
|-----------|-----------------|---------------|
| Length | Width | Qualified Qty |
| - | W < 0.02 | Ignored |
| L < 3.0 | 0.02 < W < 0.05 | 2 |
| L < 2.5 | 0.05 < W < 0.08 | |
| - | 0.08 < W | 0 |

| Size >= 5" | | |
|------------|-----------------|---------------|
| Length | Width | Qualified Qty |
| - | W < 0.02 | Ignored |
| L < 3.0 | 0.02 < W < 0.05 | 4 |
| L < 2.5 | 0.05 < W < 0.08 | |
| - | 0.08 < W | 0 |

| Item | Criterion |
|------|-----------|
|------|-----------|

Clear spots

| Size < 5" | |
|---------------------|---------------|
| Average Diameter | Qualified Qty |
| D < 0.2 mm | Ignored |
| 0.2 mm < D < 0.3 mm | 3 |
| 0.3 mm < D < 0.5 mm | 2 |
| 0.5 mm < D | 0 |

Size >= 5"

| | |
|----------------------------------|---------------|
| Average Diameter | Qualified Qty |
| D<0.2 mm | Ignored |
| 0.2 mm < D < 0.3 mm | 4 |
| 0.3 mm < D < 0.5 mm | 2 |
| 0.5 mm < D | 0 |

*Spots density: 10 mm

Polarizer bubbles

| | |
|----------------------------------|---------------|
| Size < 5" | |
| Average Diameter | Qualified Qty |
| D < 0.2 mm | Ignored |
| 0.2 mm < D < 0.5 mm | 3 |
| 0.5 mm < D < 1 mm | 2 |
| 1 mm < D | 0 |
| Total Q'ty | 3 |

| | |
|-----------------------------------|---------------|
| Size >= 5" | |
| Average Diameter | Qualified Qty |
| D<0.25 mm | Ignored |
| 0.25 mm < D < 0.5 mm | 3 |
| 0.5 mm < D | 0 |

Electrical Dot Defect

| | |
|--------------------------|---------------|
| Size < 5" | |
| item | Qualified Qty |
| Black do defect | 4 |
| Bright dot defect | 2 |
| Total Dot | 5 |

| | |
|--------------------------|---------------|
| Size >= 5" | |
| item | Qualified Qty |
| Black do defect | 5 |
| Bright dot defect | 2 |
| Total Dot | 5 |

Item

Criterion

Touch panel spot

| | |
|----------------------------------|---------------|
| Size < 5" | |
| Average Diameter | Qualified Qty |
| D < 0.2 mm | Ignored |
| 0.2 mm < D < 0.4 mm | 5 |
| 0.4 mm < D < 0.5 mm | 2 |
| 0.5 mm < D | 0 |

| | |
|-------------------------|---------------|
| Size >= 5" | |
| Average Diameter | Qualified Qty |
| D<0.25 mm | Ignored |

| | | | |
|--------------------------------|-----------------------------------|----------------|---------------|
| | 0.25 mm < D < 0.5 mm | 4 | |
| | 0.5 mm < D | 0 | |
| Touch panel White Line Scratch | Size < 5" | | |
| | Length | Width | Qualified Qty |
| | - | W< 0.02 | Ignored |
| | L < 3.0 | 0.02 < W <0.05 | 2 |
| | L < 2.5 | 0.05 < W <0.08 | |
| | - | 0.08 < W | 0 |
| | Size >= 5" | | |
| | Length | Width | Qualified Qty |
| | - | W< 0.03 | Ignored |
| | L < 5.0 | 0.03 < W <0.05 | 2 |
| | - | 0.05 < W | 0 |

13. Reliability test

| NO. | TEST ITEM | TEST CONDITION | REMARKS |
|-----|----------------------------|--|----------|
| 1 | High Temperature Storage | 80±2°C/240hours | Note 2 |
| 2 | Low Temperature Storage | -30±2°C/240hours | Note 1,2 |
| 3 | High Temperature Operating | 70±2°C/240hours | |
| 4 | Low Temperature Operating | -20±2°C/240hours | Note 1 |
| 5 | Temperature Cycle | -30±2°C~25±2°C ~80±2°C × 20 cycles (30min.) (5min.) (30min.) | Note 1,2 |
| 6 | Damp Proof Test | 60°C ±5°C × 90%RH/240hours | |
| 7 | Vibration Test | Frequency 10Hz~55Hz Amplitude of vibration : 1.5mm Sweep time: 12 min X, Y, Z 2 hours for each direction. | |
| 8 | Package Drop Test | Height:60 cm 1 corner, 3 edges, 6 surfaces | |
| 9 | ESD Test | Air: ±4KV 150pF/330Ω 5 times Contact: ±2KV 150pF/330Ω 5 times | |

| | | | |
|----|------------------|--|--|
| 10 | ESD Test for RTP | Air: ±8KV 150pF/330Ω 5 times Contact: ±4KV 150pF/330Ω 5 times | |
|----|------------------|--|--|

Note 1: Without water condensation.

Note 2: The function test shall be conducted after 2 hours storage at the room temperature and humidity after removed from the test chamber.



✉ Still stuck [How can we help](#)

Updated on April 30, 2020

← EVE 3 3.5"

EVE 3 5" →

Was this article helpful to you

Yes 2

No